

Encoder switch

TEED type

TEED02 Series



(size : $\Phi 18 \times 7.1$)

Multy Fuction Surface mount Type

■ Features

A push on switch with a clearclick operational feel
An encoder with detents and excellent operation feeling
4-directions & center push type.

■ Applications

Scroll of menu and input for Audio Visual Equipment
Level controls for car audio & navigation system
Portable audio devices,
Personal digital assistant.

■ Main Specifications

	Encoder	Push on
Rating	50mA 12V DC	
Detent (pulse)/Travel	16 detent (8 pulses)	Center:0.15mm
		4-direction:5° ±3°
Operating Force	150gf	Center: 500±50gf
		4-direction:400±50gf
Contact Resistance	1Ω Max	
Operating Life(Cycle)	30,000	

■ Products Line

TEED02 - BAWO

Products No.	Terminal Type	Guide Boss	Detent	Drawing No
BAWO	SMT	With	16	1

■ Dimensions

TEED02-BAWO

No.	3D Style	PCB pattern dimension (Unit : mm)	Circuit Diagram																																																																																																																																																																																																																																																																																																																																																																																					
1	BAWO		<p>Leaning switch</p>																																																																																																																																																																																																																																																																																																																																																																																					
			<p>Center switch</p>																																																																																																																																																																																																																																																																																																																																																																																					
			<p>Rotation switch</p>																																																																																																																																																																																																																																																																																																																																																																																					
<p>Unit:mm</p>																																																																																																																																																																																																																																																																																																																																																																																								
<p>Terminal Explanation</p> <table border="1"> <thead> <tr> <th>NO</th> <th>DESCRIPTION</th> <th>NO</th> <th>DESCRIPTION</th> </tr> </thead> <tbody> <tr> <td>①</td> <td>SWITCH COMMON A,B,C,D CENTER</td> <td>⑫</td> <td>SWITCH CENTER</td> </tr> <tr> <td>②</td> <td>ROTATION COMMON 4</td> <td>⑬</td> <td>ROTATION DETECTION 8</td> </tr> <tr> <td>③</td> <td>ROTATION DETECTION 1</td> <td>⑭</td> <td>ROTATION COMMON 1</td> </tr> <tr> <td>④</td> <td>SWITCH A</td> <td>⑮</td> <td>SWITCH C</td> </tr> <tr> <td>⑤</td> <td>ROTATION DETECTION 2</td> <td>⑯</td> <td>ROTATION COMMON 1</td> </tr> <tr> <td>⑥</td> <td>ROTATION DETECTION 3</td> <td>⑰</td> <td>ROTATION COMMON 2</td> </tr> <tr> <td>⑦</td> <td>ROTATION DETECTION 4</td> <td>⑱</td> <td>ROTATION COMMON 2</td> </tr> <tr> <td>⑧</td> <td>ROTATION DETECTION 5</td> <td>⑲</td> <td>ROTATION COMMON 3</td> </tr> <tr> <td>⑨</td> <td>SWITCH B</td> <td>⑳</td> <td>SWITCH D</td> </tr> <tr> <td>⑩</td> <td>ROTATION DETECTION 6</td> <td>㉑</td> <td>ROTATION COMMON 3</td> </tr> <tr> <td>⑪</td> <td>ROTATION DETECTION 7</td> <td>㉒</td> <td>ROTATION COMMON 4</td> </tr> </tbody> </table> <table border="1"> <thead> <tr> <th>Terminal Direction</th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> <th>5</th> <th>6</th> <th>7</th> <th>8</th> <th>9</th> <th>10</th> <th>11</th> <th>12</th> <th>13</th> <th>14</th> <th>15</th> <th>16</th> <th>17</th> <th>18</th> <th>19</th> <th>20</th> <th>21</th> <th>22</th> </tr> </thead> <tbody> <tr> <td rowspan="5">S w i t c h</td> <td>A</td> <td>●</td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>B</td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>C</td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>D</td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> </tr> <tr> <td>E (Center)</td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> </tr> <tr> <td rowspan="7">E n c o d e r (C W</td> <td>F (Normal)</td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>G</td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>H</td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>I</td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>J</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>K</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>L</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> <tr> <td>M</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>●</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> </tbody> </table>				NO	DESCRIPTION	NO	DESCRIPTION	①	SWITCH COMMON A,B,C,D CENTER	⑫	SWITCH CENTER	②	ROTATION COMMON 4	⑬	ROTATION DETECTION 8	③	ROTATION DETECTION 1	⑭	ROTATION COMMON 1	④	SWITCH A	⑮	SWITCH C	⑤	ROTATION DETECTION 2	⑯	ROTATION COMMON 1	⑥	ROTATION DETECTION 3	⑰	ROTATION COMMON 2	⑦	ROTATION DETECTION 4	⑱	ROTATION COMMON 2	⑧	ROTATION DETECTION 5	⑲	ROTATION COMMON 3	⑨	SWITCH B	⑳	SWITCH D	⑩	ROTATION DETECTION 6	㉑	ROTATION COMMON 3	⑪	ROTATION DETECTION 7	㉒	ROTATION COMMON 4	Terminal Direction	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	S w i t c h	A	●		●																				B	●								●														C	●													●									D	●																					●	E (Center)	●																						●	E n c o d e r (C W	F (Normal)		●																					G			●																				H				●																			I					●																		J						●																	K							●																L								●															M									●													
NO	DESCRIPTION	NO	DESCRIPTION																																																																																																																																																																																																																																																																																																																																																																																					
①	SWITCH COMMON A,B,C,D CENTER	⑫	SWITCH CENTER																																																																																																																																																																																																																																																																																																																																																																																					
②	ROTATION COMMON 4	⑬	ROTATION DETECTION 8																																																																																																																																																																																																																																																																																																																																																																																					
③	ROTATION DETECTION 1	⑭	ROTATION COMMON 1																																																																																																																																																																																																																																																																																																																																																																																					
④	SWITCH A	⑮	SWITCH C																																																																																																																																																																																																																																																																																																																																																																																					
⑤	ROTATION DETECTION 2	⑯	ROTATION COMMON 1																																																																																																																																																																																																																																																																																																																																																																																					
⑥	ROTATION DETECTION 3	⑰	ROTATION COMMON 2																																																																																																																																																																																																																																																																																																																																																																																					
⑦	ROTATION DETECTION 4	⑱	ROTATION COMMON 2																																																																																																																																																																																																																																																																																																																																																																																					
⑧	ROTATION DETECTION 5	⑲	ROTATION COMMON 3																																																																																																																																																																																																																																																																																																																																																																																					
⑨	SWITCH B	⑳	SWITCH D																																																																																																																																																																																																																																																																																																																																																																																					
⑩	ROTATION DETECTION 6	㉑	ROTATION COMMON 3																																																																																																																																																																																																																																																																																																																																																																																					
⑪	ROTATION DETECTION 7	㉒	ROTATION COMMON 4																																																																																																																																																																																																																																																																																																																																																																																					
Terminal Direction	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22																																																																																																																																																																																																																																																																																																																																																																		
S w i t c h	A	●		●																																																																																																																																																																																																																																																																																																																																																																																				
	B	●								●																																																																																																																																																																																																																																																																																																																																																																														
	C	●													●																																																																																																																																																																																																																																																																																																																																																																									
	D	●																					●																																																																																																																																																																																																																																																																																																																																																																	
	E (Center)	●																						●																																																																																																																																																																																																																																																																																																																																																																
E n c o d e r (C W	F (Normal)		●																																																																																																																																																																																																																																																																																																																																																																																					
	G			●																																																																																																																																																																																																																																																																																																																																																																																				
	H				●																																																																																																																																																																																																																																																																																																																																																																																			
	I					●																																																																																																																																																																																																																																																																																																																																																																																		
	J						●																																																																																																																																																																																																																																																																																																																																																																																	
	K							●																																																																																																																																																																																																																																																																																																																																																																																
	L								●																																																																																																																																																																																																																																																																																																																																																																															
M									●																																																																																																																																																																																																																																																																																																																																																																															

